

MacTable™ Assembly

The fully assembled MacTable™ looks like this >

Parts:

- top
- modesty panel
- adjustable depth shelves
- legs
- port covers
- 1/4x20 hex/phillips drive bolts: 8 per leg
- phillips drive pan head screws for modesty panel



The fully assembled MacTable™ looks like this >

Tools for assembly:

- #2 phillips driver
- 3/8 hex driver



www.smartdesks.com

800 770 7042

General Assembly

- Place the top on the floor with packing blanket or clean carpet to protect the surface. This is especially important if your MacTable has a gloss finish.
- Fasten legs to the inserts using 1/4 x 20 x 3/4 hex/Phillips drive bolts.
- Select the depth desired for the adjustable depth shelves, secure with machine screws
- Install shelves on top of the leg brackets using the common 1/4 x 20 x 3/4 hex/Phillips drive bolts.
- If a miniMac Brig™ CPU holder is being installed, orient the tail to the approach side of the center leg bracket. Install over leg bracket using the 1/4 x 20 x 3/4 hex/Phillips drive bolts.
- Spin the floor glides in all the way and use them as levelers when the table is in position for use.



Modesty Panel

- Install large pan head screws so they stand off. Pilot holes are provided.



- Stand the table upright
- Install the modesty panel by capturing the large pan head screws in the keyholes
- A driver hole is provided to tighten the screws for finished assembly



Port Caps

- Users may wish to use MacTable™ as a simple desktop, placing the iMac® or LCD monitor on the desktop. They may also wish to have work spaces that do not have computers. Port caps are provided, which simply rest in the contours of the port itself.





- **WireWonder™ Wire Manager**
- If so equipped, the WireWonder™ installs on the modesty panel with wood screws
- Power strip is surface mounted to modesty panel above the wire management channel

- J-channel is provided as standard equipment
- J-channel installs using peel and stick adhesive in the same position as WireWonder™ on the modesty panel

- **SnapChase™ Wire Manager**
- If so equipped, the SnapChase™ option is used by the IT integrator to run cables from the floor to the shelves and modesty panel.
- SnapChase™ snaps in place as shown.



www.smartdesks.com
800 770 7042